# Plaster board ceilling

A: Put the LED driver into the hole and wiring it.

B: Put the LED panel into the hole as the illustration showed.

**C: Lay down the LED panel carefully.**

D: Installation finished.

Ceiling mounted

ceiling

574mm

453mm

A: Fix these four lifting devices on the foof with screws according to the size showed in the illustration.

B: Nail M4 screws into lifting devices in the direction as the arrow shown. Attention: The screws should be nailed to the bottom.

C: Put the LED panel on the lifting devices in the direction as illustration showed.

D: Pay attention to the combination between the direction of the LED panel and lifting devices.

ceiling

Plastic expansion screws

lifting

M4 self-tapping screw

M4 screw

Panel Light

E: Loosen the M4 screws which are in the Step B to the location as illustration showed. Attention: This is the combination darwing between a single lifting device and the LED panel.

ceiling

Panel Light

F: Installation finished.

Suspension mounted

Drilling Φ5mm
Plastic expansion screws
M4 self-tapping screw
Hanging device on the wall
roof
Φ1.2 steel wire (length 1.5M)
Lifting device, when make the installation, the part arrow points to can be used to adjust the wire length
M10 screw nut
Panel Light

A: Assemble as the illustration showed.
Attention: This is the profile of a single hanger. Pls. make the installation according to this figure of structure.

Roof
Panel Light

B: Installation finished.

Illustration for LED Panel Light Installtion
## Aluminum Frame-type Mounting to Ceiling

A: Twist off one side of AL frame screws and take out from constructure.

Roof

roof

Plastic expansion screws

lifting

M4 self-tapping screw

B: Fix the AL frame to the roof with M4 screws on both sides of drilling hole as illustration shown.

C: Placing the panel light in the slot of AL frame along the level line as required.
   Please ensure the panel light is recessed in a stable and even position.

L

N

LED Driver
CE RoHS

D: Connect the power driver to the panel hidden in lamp's back. Check the safety contacts.
   Tighten the missing constructure with screws to finish the installation.

Illustration for led panel light installation
Embedded type

A. Open a mounting hole(588.5*588.5mm) onto the ceiling.

panel light

B. Fix the spring fasteners to the panel light(totally 4pcs), as showed in the illustration.
   Attention: there shall be some space of the panel light left to cover the edge of the mounting hole.

mounting hole

led driver

AC100-240V

spring fastener

panel light

C. Pls connect the power input line with the electric supply, and power output line with the panel light.
   Attention: pls turn off the power during this step.

ceiling

panel light

D. Straight all the spring fasteners to the vertical position, and put them into the ceiling to finish
   the installation.